

Konfiguracija krmilne enote / Configuration parameter configuration

Pri menjavi elektronik se vedno vgradi servisna elektronika (**343064** ali **357173**). Najprej se naredi konfiguracija (določi parametre aparata za osnovno elektroniko - tabela spodaj).

Vstop v konfiguracijo - Istočasno pritisnemo tipki S1(Start/Pause)+S3 in zavrtimo selektor iz pozicije 0 na pozicijo 1 v desno

IZBIRA POLNITVE BOBNA, IZBIRA HITROSTI CENTRIFUGE, NASTAVITEV FUNKCIJSKIH GUMBOV, NASTAVITEV IZBIRNIKA, NASTAVITEV ČRPALKE JET.

Po izstopu iz konfiguracije je aparat na izbranem programu.

Po končani konfiguraciji ugasnemo PS (selektor na poz. 0).

Nato je potrebno pognati testni program (**pridržiimo gumb S2 in S4 in zavrtimo selektor iz 0 na pozicijo v levo**) in določiti alternativo motorja po tabeli 1 (alternative motorja so označene na kadi-gle sliko ali teh. info. 4-027-1113).

For control unit replacement use always service code (**343064** and **357173**). Configuration process must be done first (to define appliance parameters for basic control units – table below).

Enter to configuration mode - Simultaneously press bottom (and keep it pressed)

S1(Start/Pause)+S3 and rotate selector knob from position 0 to position 1, direction CW.

SELECT DRUM LOAD, SELECT DRUM SPEED, SELECT FUNCTIONS OF BUTTONS,

SELECT SELECTOR TYPE, SELECT JET PUMP.

Quit configuration appliance stay on selected program. Then switch OFF the washing machine (selector on position 0).


Then run test program and define motor alternative (use table 1 – info. 4-027-1113, or see label on tub – see picture below). **Enter to test program - Simultaneously press bottom S2 +S4 and rotate selector knob from position 0 to position 1, direction CCW.**

Electronic Spin speed Load (5 is used for SLIM machines)
Platform (B, C, E1, E2)

Classic		
385503		EK C PS-10/-A3-08-5
353268	002	EK C PS-10/-A2-08-6
353278		EK C PS-10/-A2-08-7
346850	002	EK C/1 PS-10/-A2-10-5
367586		EK C/1 PS-10/-A3-10-5
363513		EK C/1 PS-10/-A3-12-5
363514		EK C/1 PS-10/-A3-14-5
353270		EK C/1 PS-10/-A3-10-6
353272		EK C/1 PS-10/-A3-12-6
353274		EK C/1 PS-10/-A3-14-6
353280		EK C/1 PS-10/-A3-10-7
353282		EK C/1 PS-10/-A3-12-7
343064		EK C/1 PS-10/-A3-14-7
357170		EK C/1 PS-10/-A3-10-8
357172		EK C/1 PS-10/-A3-12-8
357173		EK C/1 PS-10/-A3-14-8

POZICIJA IZBIRNIKA//SELECTOR POSITION				
Polnitev Drum LOAD	Centrifuga Spin SPEED	Gumbi Buttons S1, S2 and S3	Izbirnik Selector type	Črpalka Jet PUMP
1	2	1	1	1
3	2	1	1	1
3	2	1	1	1
1	3	1	1	1
1	3	1	1	1
1	5	1	1	1
1	7	1	1	1
3	3	1	1	1
3	5	1	1	1
3	7	1	1	1
3	3	1	1	1
3	5	1	1	1
3	7	1	1	1
4	3	1	1	2-15
4	5	1	1	2-15
4	7	1	1	2-15

Nalepka Motor alt./Motor label alternative (A,B,C- see table 1. info. 4-027-1113)



Alternative motorjev/Alternative motor selection (UM)

Producer	Type	Code	LOAD	Alternative	RPM	Alternati vaAlterna tive mark
Welling	HXG 30	154542	6, 7 kg	1	600	A
	HXG 40	154543	6, 7 kg		800	
	HXG 52	307327	6, 7 kg		1000-1200	
	HXG52A54.04	154545	6, 7, 8 kg		1300-1400	
	HXGM 10		SLIM		800-1200	
Selni	W35	267980	6, 7 kg	2	600	B
Ceset	MCA52/64-148/KT9	587530	6, 7 kg		800	
	MCA52/64-148/KT14	228960	6, 7 kg		800	
	MCA61/64-148/KT7	587542	6, 7 kg		1000-1200	
	MCA61/64-148/KT16	273680	6, 7, 8 kg		1300-1400	
	MCA61/52-148/KT15	314377	SLIM		800-1200	
	MCA61/52-148/KT13	163960	SLIM		1300-1400	
Ana Imep	C51.05.47.07	280350	6, 7 kg	3	600	C
	C51.05.52.05	348870	SLIM		800-1200	
Nidec	T63	587540	6, 7 kg		1000-1200	
Selni	P33	291266	6, 7, 8 kg		1300-1400	